

PRODUCT DATA SHEET

Sika® FerroGard®-715 Reba

DISCRETE ANODE FOR CORROSION PREVENTION ADJACENT TO CONCRETE REPAIRED AREAS AND IN NEW CONSTRUCTION WITH A ZINC WEIGHT OF 108 g

DESCRIPTION

Sika® FerroGard®-715 Reba is a zinc based discrete sacrificial anode placed inside a concrete repaired area in reinforced concrete structures which are corroding as a result of chloride ingress.

Sika® FerroGard®-715 Reba anodes are placed along the perimeter of the repair area and fixed to the reinforcement prior the application of a concrete repair system. The reinforcement outside the repaired area is at greatest risk owing to the passive condition of the reinforcement within the repaired area.

Sika® FerroGard®-715 Reba anodes corrode preferentially to the surrounding reinforcement offering protection against incipient anode damage.

Sika® FerroGard®-715 Reba can also be placed at specific positions on steel reinforcement stirrups when used in new construction to prevent corrosion in marine environments.

USES

Sika® FerroGard®-715 Reba may only be used by experienced professionals.

- Controlling the incipient anode effect by electrically balancing the anodic and cathodic areas of reinforcement

- Targeted treatment applied to concrete repaired areas to prevent incipient corrosion damage
 - For reinforced concrete structures such as bridges, car parks, coastal structures, industrial structures and residential high rise
 - Coastal reinforced structures both in and above the tidal zones
 - Corrosion prevention in new construction

CHARACTERISTICS / ADVANTAGES

- Sika® FerroGard®-715 Reba anodes corrode preferentially to the surrounding reinforcement, offering protection from further corrosion damage
- Protection against incipient anode effect outside of repaired areas
- No long term maintenance cost
- Strengthens passive film on reinforcement
- No rapid dissolution of activating components
- Quick installation - no additional break out
- Performance can be monitored
- Cost effective corrosion control solution

PRODUCT INFORMATION

Chemical Base	Zinc alloy compound and mortar casing of pH >14
Packaging	25 anodes per box
Appearance / Colour	Zinc anode core surrounded by an activating mortar casing with two integral conducting tie wires
Shelf Life	5 years from date of production

Storage Conditions	Product must be stored in original, unopened and undamaged sealed packaging in dry conditions at temperature between +5 °C and +30 °C. Always refer to packaging. Do not allow contact with oxidizing materials.
Dimensions	70mm x 55mm x 35mm
Zinc Weight	108 g

TECHNICAL INFORMATION

Current Density	> 0,2–2 mA/m ² * in corrosive environment * Dependent on local conditions, including chloride concentration, concrete properties, humidity and temperature.
------------------------	---

SYSTEM INFORMATION

System Structure	Sika® FerroGard®-715 Reba is part of the Sika® FerroGard®-700 anode series that consists of the following anodes:								
	<table> <tr> <th>Name</th><th>Zinc content</th></tr> <tr> <td>Sika® FerroGard®-710 Reba</td><td>60 g</td></tr> <tr> <td>Sika® FerroGard®-715 Reba</td><td>108 g</td></tr> <tr> <td>Sika® FerroGard®-720 Reba</td><td>180 g</td></tr> </table>	Name	Zinc content	Sika® FerroGard®-710 Reba	60 g	Sika® FerroGard®-715 Reba	108 g	Sika® FerroGard®-720 Reba	180 g
Name	Zinc content								
Sika® FerroGard®-710 Reba	60 g								
Sika® FerroGard®-715 Reba	108 g								
Sika® FerroGard®-720 Reba	180 g								

BASIS OF PRODUCT DATA

All technical data stated in this Product Data Sheet are based on laboratory tests. Actual measured data may vary due to circumstances beyond our control.

LIMITATIONS

In order that suitable current flow and lifetime be achieved from the Sika® FerroGard®-715 Reba anode, certain practical considerations must be taken into consideration:

- The repair material cover for Sika® FerroGard®-715 Reba unit must be at least 20 mm.
- Concrete repairs must be undertaken in accordance to an acknowledged national standard such as EN 1504.
- Any discontinuous reinforcement must be either electrically bonded or electrically isolated from the system negative.
- The time to achieve passivity will be dependent on site conditions. Depolarisation of treated reinforcement will be slower in moist conditions.
- Design of the galvanic protection system must be undertaken by an experienced qualified corrosion design engineer.
- Installation must be carried out in accordance with engineers design and specification.
- When used in new construction the concrete cover must be at least 50 mm.

ECOLOGY HEALTH AND SAFETY

This product is an article as defined in article 3 of regulation (EC) No 1907/2006 (REACH). It contains no substances which are intended to be released from the article under normal or reasonably foreseeable conditions of use. A safety data sheet following article 31 of the same regulation is not needed to bring the product to the market, to transport or to use it. For

safe use follow the instructions given in this product data sheet. Based on our current knowledge, this product does not contain SVHC (substances of very high concern) as listed in Annex XIV of the REACH regulation or on the candidate list published by the European Chemicals Agency in concentrations above 0.1 % (w/w)

APPLICATION INSTRUCTIONS

APPLICATION

Reference must also be made to the full Method Statement which is summarised below:

Control of incipient anodes

Within the repair area where the concrete has been removed, locate the Sika® FerroGard®-715 Reba anodes along the perimeter edges of the repair at spacing's determined by the design engineer based on the steel density.

After pre-soaking the individual Sika® FerroGard®-715 Reba anodes, they are attached parallel or beneath the cleaned reinforcement in the location of the anodes using the conducting ties wires.

Electrical continuity of the Sika® FerroGard®-715 Reba anode conductors and the reinforcement must be confirmed. The Sika® FerroGard®-715 Reba units must be then be encased in the relevant Sika® low resistivity bridging mortar ensuring complete coverage of the anode surface. The appropriate Sika® concrete repair system is then applied with the repair area once the bridging mortar has stiffened sufficiently to prevent movement of the anodes.

The Sika® FerroGard®-715 Reba anode installation can be monitored using half-cell potential surveys, current outputs and reinforcement corrosion rate measurements.

Corrosion prevention in new construction

Sika® FerroGard®-715 Reba anodes are attached to the reinforcement by the integral tie wires at regular spacing's (refer to the Method Statement). They must be properly fixed to the bar with additional plastic tie wires to prevent the anodes being displaced during concrete casting.

LOCAL RESTRICTIONS

Please note that as a result of specific local regulations the performance of this product may vary from country to country. Please consult the local Product Data Sheet for the exact description of the application fields.

LEGAL NOTES

The information, and, in particular, the recommendations relating to the application and end-use of Sika products, are given in good faith based on Sika's current knowledge and experience of the products when properly stored, handled and applied under normal conditions in accordance with Sika's recommendations. In practice, the differences in materials, substrates and actual site conditions are such that no warranty in respect of merchantability or of fitness for a particular purpose, nor any liability arising out of any legal relationship whatsoever, can be inferred either from this information, or from any written recommendations, or from any other advice offered. The user of the product must test the product's suitability for the intended application and purpose. Sika reserves the right to change the properties of its products. The proprietary rights of third parties must be observed. All orders are accepted subject to our current terms of sale and delivery. Users must always refer to the most recent issue of the local Product Data Sheet for the product concerned, copies of which will be supplied on request.

Sika South Africa (Pty) Ltd

9 Hocking Place,
Westmead, 3608
South Africa
Phone +27 31 792 6500
www.sika.co.za



Product Data Sheet

Sika® FerroGard®-715 Reba
August 2026, Version 04.01
020303090010000024

SikaFerroGard-715Reba-en-ZA-(08-2026)-4-1.pdf